


42mm
42mm
42mm
42mm
42mm
42mm

BASIC INFORMATION



This product can connect to classic wall switches and easily convert the connected device into a smart one. It does not interfere with your traditional switch. Additionally, it supports Zigbee protocol and allows for full control of connected appliances with timers, schedules, and countdown. Install to enhance your convenience and enjoy living in a conscious house.

1


WARNINGS & SAFETY INSTRUCTIONS

The following must be read, kept, and observed before installation:


- Installation must be carried out by a qualified electrician in accordance with local regulations.
- Keep the device out of the reach of children and away from water and damp or hot environments.
- Install the device away from strong signal sources, such as microwave ovens, which may cause signal interruption resulting in abnormal device operation.
- Obstruction by concrete walls or metallic materials may reduce the effective operation range of the device and should be avoided.
- Do not attempt to disassemble, repair, or modify the device by yourself.

2

MOUNTING THE DEVICE




1 Fix the module behind the traditional switch




2 Connect the L, N, loads and switches as per the diagram

3

CONFIGURATION



1 Download the App
Search for TIS Control & download the app.




2 Set up your hub (if not already set in the application).


4

2 Go to Settings, and enter the default username and password.

Username: user
Password: tis777





4 Go to the TIS-BEE configuration button, and follow the instructions.



5

5 Add the Device
In the TIS-Bee configuration, press Add Device. Then, follow the instructions to add the device using the 2 available methods.

a. Scan QR Method b. Search Method


Select whichever method you prefer, and follow the instructions on the app.

6

45mm

42mm
42mm
42mm
42mm
42mm

TECHNICAL SPECIFICATIONS



Communication Protocol
Zigbee® 3.0 Network

Operation temp.
-10°C - +40°C

Operation range
≤200 m

Voltage
90-250V AC


Current
10A max

IP rating
IP20


7

RESET TO FACTORY DEFAULT

Push wall switch
Press the switch button 10 times until you hear beep sounds continuously.




Rocker switch
Press the switch button 20 times (ON/OFF cycle for 10 times) until you hear beep sounds continuously.



8

Module's reset button



Long press the button on the module for 15 seconds to hear the beep sounds continuously.


9

TROUBLESHOOTING

Problem	Possible Cause	Solution
Unable to pair	Module not in pairing mode	Reset the Module to factory mode.
	Module is away from the hub, or there are obstacles.	Move Module closer to the hub.
	Module is connected to another hub network.	Reset the module to factory default.

10

TIS BEE User Manual
2-Gang Switch Module



Product specifications, size, shape, and prices are subject to change without notice, and actual product appearance may differ from that depicted on the packaging.

TIS TIS CONTROL LIMITED

RM 1502-p9 Easey Comm Bldg 253-261
Hennessy Rd Wanchai, Hong Kong

www.tiscontrol.com

CE

Please read the user manual carefully before operation

45mm