


70mm
70mm
70mm
70mm
70mm
70mm

BASIC INFORMATION



This UK-standard mini plug is just what you need to make your home smart. This is the best solution to create a smart home where devices can be set to turn ON/OFF both automatically and manually. It helps you control electrical appliances remotely and over phone. Install to switch appliances ON/OFF, define preset functions, and measure energy consumption from any spot around the world.

1


WARNINGS & SAFETY INSTRUCTIONS

The following must be read, kept, and observed before installation:

- The plug is for indoor use only.
- Improper use or installation of the device can cause **SERIOUS INJURY, DEATH, or LOSS/DAMAGE OF PROPERTY.**
- Do not use in a manner other than what is outlined in this document.
- Turning the device on/off more often than once in two seconds can shorten its lifetime.
- Do not try to open or to repair the device by yourself. Leave device repair to a technician or other expert.
- Avoid overloading the device. Observe the recommended limit.

2

MOUNTING THE DEVICE




Simply plug into a wall outlet.


3

CONFIGURATION

1 Download the App
Search for TIS Control & download the app.




2 Set up your hub (if not already set in the application).




4

3 Go to Settings, and enter the default username and password.

Username: user
Password: tis777




4 Go to the TIS-BEE configuration button, and follow the instructions.




5

5 Add the Device
In the TIS-Bee configuration, press Add Device. Then, follow the instructions to add the device using the 2 available methods.



a. Scan QR Method




b. Search Method




Select whichever method you prefer, and follow the instructions on the app.

6

70mm
70mm
70mm
70mm
70mm
70mm

LED BEHAVIOR



LED Status	Description
 LED flashes once a second for 60 seconds	Network is connecting.
 LED stops flashing	Network is working properly.
 LED flashes quickly	Factory reset is being finalized.

7

TECHNICAL SPECIFICATIONS

Voltage
240V~/50Hz

Maximum Load
3120W

Operating Frequency
2400-2483.5MHz

RF output power
<20 dBm

Product Dimensions
64mm×60mm×60mm

Communication Protocol
Zigbee® 3.0 Network

Plug Format
Type G Square plug (UK standard)


Operating humidity
<80%

Item Weight
70g


8

RESET TO FACTORY DEFAULT

1 Press the button on the Smart Plug for at least 5 seconds, until the red LED starts to blink rapidly.



2 After that, the green LED will blink once a second, indicating that it can be paired to a Gateway again.



9


TROUBLESHOOTING

Problem	Possible Cause	Solution
Unable to pair	Plug not in pairing mode	Reset the plug to factory mode.
	Detector is away from the hub, or there are obstacles.	Move detector closer to the hub.
	The search for a gateway has timed out.	Short press on the button to restart it.
	Detector is connected to another hub network.	Reset the detector to factory default.

10

TIS BEE Zigbee Smart Plug

User Manual




CE

Product specifications, size, shape, and prices are subject to change without notice, and actual product appearance may differ from that depicted on the packaging.

TIS TIS CONTROL LIMITED

RM 1502-p9 Easey Comm Bldg 253-261
Hennessy Rd Wanchai, Hong Kong

www.tiscontrol.com



Please read the user manual carefully before operation